



## Lynx 3<sup>AP</sup> Quick Set-Up Instructions:

- Step 1: Plug the USB cable from the Lynx 3<sup>AP</sup> to the router. If necessary, use the provided active USB extension cable.
- Step 2: Plug in the wireless router.
- Step 3: Wait 2-3 minutes.
- Step 4: Search available networks and Connect to 'Lynx 3AP' (or 'Alfa\_AP').
- Step 5: Open a web browser and type in '192.168.2.1' as the web address.
- Step 6: Type in 'admin' for both User Name and Password and you will get to the homepage.



- Step 7: Click 'Easy Setup' tab.



(continued on next page . . .)

Step 8: Click 'USB Wireless adapter'.



Step 9: Click the 'Site Survey' button.



Step 10: If screen is blank, click 'Rescan' button.



(continued on next page . . .)

Step 11: The Lynx 3<sup>AP</sup> will scan for networks – click on the small circle next to the network you would like to connect to and the click the ‘Select’ button at the bottom of the page.

Site Survey

Results in the grid can easily be sorted by a single column by clicking on the column heading. Clicking on a column heading will initially sort the results by the values in the column in sequence. If you click on the heading of column that is already the sort sequence then the sequence of the sorting will be reversed.

<input checked="" type="checkbox"/>	VAP	00:11:45:02:48:07	54 Mb/s	89/100	1	None	None	Infrastructure
<input type="checkbox"/>	Alienware_E1	00:0E:85:F7:13:05	54 Mb/s	60/100	1	TKIP	WPA1	Infrastructure
<input type="checkbox"/>	WLAN	00:05:CA:43:19:18	54 Mb/s	37/100	1	None	None	Infrastructure
<input type="checkbox"/>	WWi	00:0C:CA:30:C6:16	54 Mb/s	89/100	8	AES/TKIP	WPA2	Infrastructure
<input type="checkbox"/>	TP-LINK	94:0C:8D:00:ED:85	54 Mb/s	85/100	6	WEP	OPEN/SHARED	Infrastructure
<input type="checkbox"/>	Kentata2	00:08:54:AE:CD:08	54 Mb/s	85/100	11	AES/TKIP	WPA1	Infrastructure
<input type="checkbox"/>	guest	00:13:0E:41:60:21	54 Mb/s	55/100	11	WEP	OPEN/SHARED	Infrastructure
<input type="checkbox"/>	WLAN	00:09:CA:00:44:84	54 Mb/s	49/100	11	WEP	OPEN/SHARED	Infrastructure
<input type="checkbox"/>	ALFA	00:22:2D:B4:E3:26	54 Mb/s	95/100	14	None	None	Infrastructure
<input type="checkbox"/>	Yok_Itavao_AP	00:03:2F:31:A2:0E	54 Mb/s	47/100	11	WEP	OPEN/SHARED	Infrastructure
<input type="checkbox"/>	3Q router	00:0C:CA:26:0C:82	54 Mb/s	51/100	11	None	None	Infrastructure
<input type="checkbox"/>	employee	00:13:0E:41:6B:20	54 Mb/s	58/100	11	WEP	OPEN/SHARED	Infrastructure

Select Rescan Close

Step 12: The screen will show the connected SSID and BSSID. Click ‘Next’. If connecting to a secured network, enter the password in the ‘Pass Phrase’ box and then click ‘Next’.

System Configuration

Connection Mode: [AutoConnect P (WUP) 2]

ESSID: [VAP] BSSID (optional): [00 11 45 02 48 07]

Network Type: [Infrastructure] [Site Survey]

Security Policy: [None]

Security Mode: [Open]

Next



(continued on next page . . .)

Step 13: After reboot, the next screen will show connected status and the USB wireless adapter information.



Step 14: That's it! You're connected!

Step 15: If the 'Wizard Success' message does not appear, search available networks and reconnect to 'Lynx 3AP' (or 'Alfa\_AP').

(end of document)